

LED MANAGER JBSYSTEMS

Código 127BE/4930
EAN13: 5420025649308

Descripción

La fuente de alimentación 300W/24V es extremadamente versátil para todas las clases de proyectores pasivos RGB LED

Diversos modos autónomos:

Modo Fixed colors: acceso inmediato a 9 colores preprogramados

Modo Static chase: 12 diversas persecuciones de color con control manual de la velocidad

Modo Sound chase: 12 diversas persecuciones de color con accionar audio

Spectrum mix: 32 diversos colores spectrum mix, incluyendo hermosas transiciones de color

Todas las funciones se pueden controlar directamente con el LED Manager o con el remoto opcional LEDCON-01

Reloj incorporado con baterías de reserva y 3 contadores de tiempo programables on/off

Necesita 4 canales de DMX: Ch1=rojo, Ch2=verde, Ch3=azul, Ch4=dimmer/estroboscópico

Información Técnica

Power Input: AC 230V~ 50Hz Fuse: 6,3A slow blow (20mm glass) Backup batteries: 3x 1,2V AA-type NiMH rechargeable batteries (optional) Output voltage to LEDs: DC 24V common anode Output power to LEDs: 2x 150W max. (Total = 300W max.)

Red: 2x 50W max. (Total = 100W max.)

Green: 2x 50W max. (Total = 100W max.)

Blue: 2x 50W max. (Total = 100W max.)

DMX connections: 3pin XLR (DMX-512 standard) DMX channels: 4 (CH1: red, CH2: green, CH3:blue, CH4:dimmer/strobe) Audio input: None, internal microphone Size: 330 x 202 x 106cm (see drawing below) Weight: 6,6kg



Fotos

